

Phase Indicators

KEW 8031F



- KEW8031F is designed to check phase sequence.
- Lamps provided on the unit will also tell you if a phase is open.
- Can check a wide range of 3-phase power source from 110V to 600V.
- Sealed against dust, the unit ensures trouble-free performance.
- Small, Lightweight and portable.
- Designed for maximum ease of operation and ruggedness.
- No exposed metal parts, Safety features are incorporated including the instant push button switch operation.

Operational Voltage	110 - 600V AC
Fuse	0.5A/600V (F)
Time limit for continuous	>500V : within 5 minutes
Frequency response	50Hz/60Hz
Cord	1.5m (R:red S:white T:blue)
Dimensions	106(L) × 75(W) × 40(D)mm
Weight	350g approx.
Included Accessories	9094 (Carrying Case), Instruction Manual